

WHAT IS CLAIMED IS

1 1. A lamp-control circuit, comprising:
2 a power factor corrector;
3 a digitally controlled ballast, comprising power devices and coupled to the
4 power factor corrector, the ballast operable to power a lamp;
5 a current feedback loop, coupled between at least one of the power devices and
6 the digitally controlled ballast; and
7 a voltage feedback loop, coupled between the lamp and the digitally controlled
8 ballast.

1 2. The lamp-control circuit of claim 1, wherein:
2 the power factor corrector is operable to generate AC input current and voltage
3 essentially in phase with each other.

1 3. The lamp-control circuit of claim 1, the digitally controlled ballast
2 comprising:
3 a controller, coupled to the power factor corrector by a DC link; and
4 an output stage, comprising the power devices and coupled to the controller.

1 4. The lamp-control circuit of claim 3, the controller comprising:
2 a digital controller, coupled to the power factor corrector by the DC link; and
3 a power device driver, controlled by the digital controller and configured to
4 drive the output stage.

1 5. The lamp-control circuit of claim 4, wherein:
2 the digital controller and the power device driver are integrated on a chip.

1 6. The lamp-control circuit of claim 4, wherein the output stage comprises:
2 two power devices coupled in series, having an output terminal coupled in
3 between the power devices; wherein
4 the power devices are selected from the group of power MOS-FETs and power
5 bipolar junction transistors.

1 7. The lamp-control circuit of claim 6, wherein:
2 the current feedback loop comprises a current sensor, coupled to the two power
3 devices, thereby operable to sense the current of at least one power device.

1 8. The lamp-control circuit of claim 7, wherein:
2 the current sensor is one of a current sensing resistor and a current transformer,
3 coupled in series with the two power devices; and
4 the current feedback loop comprises a resistor-capacitor filter, coupled between
5 the current sensing resistor and the digital controller.

1 9. The lamp-control circuit of claim 4, wherein
2 the voltage feedback loop comprises a voltage sensor, coupled to the lamp,
3 thereby operable to sense the voltage of the lamp.

1 10. The lamp-control circuit of claim 9, wherein:
2 the voltage sensor is a voltage sensing resistor, coupled to the lamp; and
3 the voltage feedback loop comprises a resistor-capacitor filter, coupled between
4 the voltage sensing resistor and the digital controller.

1 11. The lamp-control circuit of claim 4, the digital controller comprising:
2 a comparator, configured to compare a signal of at least one of the current
3 feedback loop and the voltage feedback loop to a reference voltage.

1 12. The lamp-control circuit of claim 1, wherein:

2 the digitally controlled ballast is configured to receive external commands while
3 in operation.

1 13. The lamp-control circuit of claim 1, wherein:
2 the lamp-control circuit is operable to power a lamp selected from the group of
3 cold cathode lamps, fluorescent lamps, high pressure discharge lamps, metal halide
4 lamps, high intensity discharge lamps, and gaseous lamps.

1 14. The lamp-control circuit of claim 1, wherein:
2 the lamp-control circuit is operable to control more than one lamps, wherein
3 the lamps are coupled to corresponding voltage feedback loops.

1 15. A method of operating a lamp-control circuit, the circuit comprising a
2 digital controller, an output stage, a current feedback loop, and a voltage feedback loop,
3 the method comprising:
4 receiving one of a current feedback signal and a voltage feedback signal by the
5 digital controller;
6 generating a digital control signal in response to the received signal by the
7 digital controller; and
8 powering a lamp by the output stage according to the generated digital control
9 signal.

1 16. The method of claim 15, the generating of a digital control signal
2 comprising:
3 generating at least one of a pulse width modulated and a pulse frequency
4 modulated control signal by the digital controller.

1 17. The method of claim 16, wherein generating a pulse frequency
2 modulated signal comprises:
3 generating a counter signal by increasing a voltage level in accordance with
4 increasing counter values; and

5 generating a control voltage.

1 18. The method of claim 17, wherein the generating of a digital control
2 signal comprises:

3 generating a “High” value for the digital control signal when the counter signal
4 exceeds the control voltage; and

5 generating a “Low” value for the digital control signal when the control voltage
6 exceeds the counter signal.

1 19. The method of claim 18, the output stage comprising a first and a second
2 power device, wherein powering the lamp comprises:

3 opening the first power device and closing the second power device, when the
4 digital control signal is High; and

5 closing the first power device and opening a second power device, when the
6 digital control signal is Low.

1 20. The method of claim 16, wherein generating a pulse width modulated
2 control signal comprises:

3 generating a counter signal by increasing a voltage level in accordance with
4 increasing counter values; and

5 generating a control voltage, varying in time.

1 21. The method of claim 16, wherein powering the lamp comprises:

2 pre-heating the lamp by powering the lamp at a pre-heating frequency, wherein
3 at the pre-heating frequency the voltage across the lamp is below an ignition voltage.

1 22. The method of claim 21, wherein powering the lamp comprises:

2 igniting the pre-heated lamp by powering the lamp at a lower ignition frequency,
3 wherein at the ignition frequency the voltage across the lamp exceeds an ignition
4 voltage.

1 23. The method of claim 15, wherein the method comprises:
2 sensing a current of the output stage by the current feedback loop;
3 generating the current feedback signal according to the sensed current;
4 receiving the current feedback signal by the digital controller; and
5 controlling the frequency of the digital control signal to control the sensed
6 current into a predetermined range.

1 24. The method of claim 15, wherein powering the lamp comprises:
2 sensing a voltage of the lamp by the voltage feedback loop;
3 generating the voltage feedback signal according to the sensed voltage;
4 coupling the voltage feedback signal into the digital controller; and
5 controlling the frequency of the digital control signal to control the sensed
6 voltage into a predetermined range.

1 25. The method of claim 15, the method comprising:
2 generating the digital control signal to control at least one of a lamp preheating
3 time, a soft-start time, an ignition time, a powering frequency and an ignition frequency.

1 26. The method of claim 15, the method comprising:
2 generating the digital control signal to provide at least one of over-load
3 protection, over-current protection, short protection, and lamp malfunction protection.

1 27. The method of claim 15, the method comprising at least one of
2 receiving external control commands by the digital controller during the operatio
3 of the lamp-control circuit; and
4 sending status signals by the digital controller during the operation of the lamp-
5 control circuit.

1 28. The method of claim 27, the receiving the external control commands
2 comprises:
3 receiving external commands to vary a frequency of the digital control signal to

- 4 digitally control the brightness of the lamp.